

#### **About Dimmer Compatibility**

The dimmers listed below were tested with the specified Prowell LED drivers. We are constantly adding to our list of compatible dimmers.

This chart describes the lowest measured electrical output when using the dimmer/driver combination. Some dimmers have wider dimming range. Zero (0%) means dim to off. One percent (1%) and five percent (5%) provide good dimming range. However, these percentages do not accurately describe the perception of the lamp, which is subjective to the individual viewer.

This compatibility list also takes into account other quality considerations such as flicker or pulsation. We do not recommend dimmers with these issues. In those cases where a dimmer is not compatible, we have suggested an alternate Prowell product.

Minimum Dimming Percentage								
DIMMER TYPE	M20DC24	M40DC24	M60DC24	M100DC24	M150DC24	M200DC24	M300DC24	
<b>Lutron Caseta, Wireless</b> PD-6WCL (MLV	D: t 00/	Approved Dims to 0%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	
<b>Lutron Maestro, Wireles</b> MRF2-6CL (MLV	Approved	Approved	Approved	Approved	Approved	Approved	Approved	
Legrand Adorne ADWR700MMTU (MLV	Approved	Approved	Recommend prowell's E-Series Driver	Recommend prowell's E-Series Driver	Not Recommended	Not Recommended	Not Recommended	
Lutron Radio RA 2 RRD-6ND (MLV	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	
<b>Lutron Maestro</b> MA-600 (MLV	Not Recommended	Not Recommended	Recommend prowell's E-Series Driver	Recommend prowell's E-Series Driver	Not Recommended	Not Recommended	Not Recommended	
<b>Legrand Adorne</b> ADTP703TUW4 (MLV	Approved	Approved	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	
<b>Leviton Decore Smart</b> DW6HD (MLV	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	
<b>Lutron Nova T</b> NTLV-600 (MLV	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	
	Note: N	л-Series support	ts MLV (Forward	l-Phase) dimmi	ng only.			



Minimum Dimming Percentage								
DIMMER TYPE	M20DC24	M40DC24	M60DC24	M100DC24	M150DC24	M200DC24	M300DC24	
<b>Leviton illumatech</b> IPMO6 (MLV)	Recommend prowell's E-Series Driver							
<b>Lutron Ariadni</b> AYLV-600P (MLV)	Approved							
<b>Lutron Diva</b> DVLV-600P (MLV)	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 1%					
<b>Lutron Caseta, Wireless</b> PD-10NXD (MLV)	Approved							
<b>Lutron Diva</b> DVCL-153P (MLV)	Approved Dims to 1%	Approved Dims to 1%	Approved	Approved	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	
Lutron Maestro  MA-PRO (MLV/ELV)  MLV Result	Approved							
Lutron Radio RA2 RRD-PRO (MLV/ELV) MLV Result	Approved							
<b>Lutron Caseta, Wireless</b> PD-5NE (MLV/ELV) MLV Result	Approved							
<b>LeGrand Tru-Universa</b> RH703PTUW (MLV Mode)	Approved	Approved	Not Recommended	Not Recommended	Approved	Approved	Approved	
<b>LeGrand Adorne</b> AADTP700RMTUM1 (MLV)	Not Recommended							
Lutron Maestro+ Motion Sensor MSCL-OP153MH	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 1%					
Lutron Caseta Smart Home Plug-in PD-3PCL	Approved							
	Note: N	1-Series support	ts MLV (Forward	l-Phase) dimmii	ng only.			



Minimum Dimming Percentage									
DIMMER TYPE	M20DC24	M40DC24	M60DC24	M100DC24	M150DC24	M200DC24	M300DC24		
<b>Lutron Maestro</b>	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
MACL-153P	Dims to 0%	Dims to 0%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%		
<b>Lutron Maestro IR</b>	Not	Not	Not	Not	Not	Not	Not		
MIRLV-600P	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended		
<b>Lutron Maestro</b>	Not	Not	Not	Not	Not	Not	Not		
MSC-1000M	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended		
<b>Lutron Toggle</b>	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
TGCL-153P	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 1%	Dims to 1%	Dims to 1%		
<b>Lutron Sunnata Touch</b>	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
STCL-153P	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 1%	Dims to 1%	Dims to 1%		
<b>Leviton Sureslide</b> 6674	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved	Approved	Approved	Approved		
<b>Leviton Toggle Slide</b>	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
TSM10-1LI	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%		
<b>leviton Decora Smart</b>	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
DW1KD-1BZ	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 0%	Dims to 0%		
<b>leviton Decora Digital</b> DDMX1-BLZ	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
<b>leviton Decora Digital</b> DDL06-1LZ	Not	Not	Not	Not	Not	Not	Not		
	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended		
<b>leviton Decora Slide</b> DSM10	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved	Approved	Approved		
<b>leviton Decora Slide</b>	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
DSL06-1LZ	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%		
<b>GE Z-wave plus</b>	Approved	Approved	Approved	Approved	Approved	Approved	Approved		
ZW3005	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%	Dims to 1%		
HALO Smart	Not	Not	Not	Not	Not	Not	Not		
HIWAC1BLE40AWH	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended	Recommended		
	Note: N	N-Series support	ts MLV (Forward	l-Phase) dimmi	ng only.				



Minimum Dimming Percentage								
DIMMER TYPE	M20DC24	M40DC24	M60DC24	M100DC24	M150DC24	M200DC24	M300DC24	
<b>WeMo WiFi</b> F7C059	Approved							
<b>Insteon Smart</b> 2477DH	Not Recommended							
<b>TP-Link Kasa Smart</b> HS220P3	Approved Dims to 1%							

Note: M-Series supports MLV (Forward-Phase) dimming only.